

3000 WATTS

GP SERIES

Portable Inverter Generator

GENERAC®



GP3000i Portable Inverter Generator featuring PowerRush™ Advanced Technology

GP3000i

PORTABLE INVERTER GENERATOR

Light and quiet power on the go.

Power whenever and wherever you need it, the Generac GP3000i inverter featuring new, advanced PowerRush™ technology delivers over 50 percent more starting capacity for your RV essentials and other motor-driven equipment—so you can do more with less.* Quiet inverter power—perfect for outdoor activities in a compact and lightweight solution.

OVER 50% MORE STARTING CAPACITY

with new, advanced PowerRush™ technology so you can do more with less*

QUIET INVERTER POWER

that reduces sound emissions and provides optimal performance

EASY-TO-CARRY

with a compact and lightweight built-in handle

ONE SIMPLE-TO-USE DIAL

that integrates start/run/stop functions with PowerDial™



POWERRUSH™

DOUBLE YOUR POWER

PARALLEL KIT (#7668-0)

A Generac parallel kit allows you to double your power when pairing two inverter generators together with the same output.† Parallel kit sold separately.

*Increases electrical current upon demand; above rated output when starting electric motors.

†Connect any two Generac 3000 or 3500 Series* inverters for twice the power. Applies when pairing two inverter generators with the same output. Parallel kit sold separately.



CONTROL PANEL FEATURES



- GENERATOR STATUS LIGHTS**
Ready, overload and low oil
- ECONOMY MODE**
Provides excellent fuel economy and noise reduction
- USB OUTLETS**
Charge mobile devices including smartphones and tablets
- PARALLEL READY**
Connect two inverters together for twice the power (parallel kit sold separately)

HOW MUCH POWER DO YOU NEED?

Sizing a portable generator is easy. Check out this example:

- CHOOSE WHICH DEVICES YOU WANT TO POWER AT THE SAME TIME.**
- RECORD THE RUNNING WATTS LISTED FOR EACH DEVICE. IF YOUR DEVICE ONLY LISTS AMPS, MULTIPLY THE AMPS BY 120V TO GET WATTAGE. EX. 15A X 120V = 1800 WATTS**
- ADD THE RUNNING WATTS TOGETHER FOR ALL DEVICES. THIS IS THE MINIMUM RUNNING WATTAGE REQUIREMENT FOR YOUR NEEDS.**

DEVICE	RUNNING WATTS	GENERATOR SIZE
RV Air Conditioner (13,500 BTU) [†]	1250	Minimum running Watts for your needs ↓ 2300 RUNNING WATTS
LED/LCD Television	120	
Blue Ray Player	15	
Slow Cooker	250	
Cell Phone Charger	10	
RV Microwave	600	
Total	2245	

[†]Motor load, demands higher Watts at start-up.
Watts listed are approximate. Check your appliance for actual requirements. Total wattage requirements assumes intermittent starting of devices.

	DEVICE	RUNNING WATTS
RECREATION	RV Air Conditioner (13,500 BTU) [†]	1250
	Cell Phone Charger	10
	Box Fan - 20"	100
	Tablet	20
	Blue Ray Player	15
	LED/LCD Television	120
	Slow Cooker	250
	Laptop Computer	75
	Coffee Maker	900
	RV Microwave	600
JOBSITE	Blender	1000
	Hair Dryer	1500
	Lithium Ion Battery Charger	360
	Air Compressor [†]	1000
	Circular Saw [†]	1400
	Hand Drill [†]	600
	Belt Sander [†]	1200
	Reciprocating Saw [†]	1440
	Table Saw [†]	1800
	Airless Paint Sprayer	1080
HOUSEHOLD	Wet Dry Vac	900
	Quartz Halogen Work Light	1000
	Refrigerator/Freezer [†]	700
	Lights	600
	Desktop Computer	400
	Sump Pump [†]	2100
	Toaster	1200
	Window AC (12,000 BTU) [†]	3250

GP3000i

PORTABLE INVERTER GENERATOR



SPECIFICATIONS

SERIES	GP3000i
Model #	7129
Configuration	50ST/CSA
Running Watts	2300
Starting Watts	3000
Engine Type	Generac OHV
Engine Displacement	149cc
Starting Method	Recoil Pull Start
Low Oil Shutdown	Yes
Fuel Tank Capacity (Gallons)	1.06
Run Time @ 50% Load	4.5 hrs
Run Time @ 25% Load	5.8 hrs
Rated Voltage	120V
Low Total Harmonic Distortion (THD)	Less than 3%
Outlets	(1) 120V 20A 5-20R Duplex, (1) 120V 30A L5-30R Twist Lock, (2) USB
Parallel Ready	Yes
Handle Style	Single, Molded Into Enclosure
Dimensions (L" x W" x H")	22.2 X 13.3 X 18.4
Product Weight	59.5 lbs
Warranty - Residential	3 Year Limited
Warranty - Commercial	1 Year Limited

All portable specifications and models subject to change. Please consult factory for availability.

PARALLEL KIT

Model # (Configuration)	7668-0
Receptacle Type	(1) 120V 50A 14-50R, (1) 120V 30A TT-30R (RV)
Covered Outlets	Yes
Rated 120 VAC Amperage	50 Amp
AC Rated Voltage	120 V
Warranty - Residential	90 Day Limited
Warranty - Commercial	90 Day Limited
Dimensions (L x W x H)	9.84" x 4.33" x 8.27"

GENERAC®